

## Allen-Bradley® N-Series Brushless motor with Copley Xenus and Accelus Amplifiers



### Features

- Torque 2 to 47 lb-in continuous.
- Speeds to 6000rpm
- Sinusoidal Commutation
- Brake option

Stall Torque Lb-in	rpm	Buss Voltage Vdc	Stall Current	Motor Model	Amplifier Models
2	6000	75	2.5	N-2302-1	ASP-090-09, XSL-230-18
4	5000	150	2	N-2304-1	ASP-180-09, XSL-230-18
6	6000	150	4	N-3406-2	ASP-180-18, XSL-230-18
12	3300	150	4.1	N-3412-2	ASP-180-18, XSL-230-18
14	2800	150	3.9	N-4214-2	ASP-180-18, XSL-230-18
20	6000	210	8	N-4220-2	XSL-230-36
30	5000	250	8.8	N-5630-2	XSL-230-36
37	3800	250	8.4	N-5637-2	XSL-230-36
47	3100	250	8.4	N-5647-2	XSL-230-36

**Xenus to N-Series  
WIRING**

